


Scimagic New Multi Frequency Universal Remote Control Duplicator



Best Copy Position

Feature

Auto scan type

Multi frequency 280-868mhz
Duplicate rolling code and fixed code
Up to 4 different remotes in 1

Programming

A) Standard

1. Press and hold button 1 and press button 2 four times at same time
2. Release 2 buttons till LED flashed once every three seconds
3. Put original remote in the front of new remote (as closer as possible), press the original remote button which need to be copied until the LED of new remote flash quickly
(LED have regular flashes)
4. Press the button of New remote that you want to use to save the code
5. If you do not copy successfully, please repeat above steps
6. To duplicate a second button, repeat the above steps

AMC: Automatic Matching Code

BFT

- 1) Press and hold button 1 and press button 2 four times at same time, Release 2 buttons till LED flashed once every three seconds
- 2) Put original remote in the front of new remote (about 2-3cm), press and hold the original remote button which need to be copied until the LED will turn on with a fixed light and then emits a double flash very 2 seconds
- 3) Pressing the hidde button or the button 1 and 2 simultaneously in the new models (transmit the seed code of original BFT remote)
- 4) Now the led will flash quickly, press the new remote button that you want to save the code, the LED will off
- 5) Now active the remote with AMC procedure

FAAC and GENIUS

Note: your original remote conrol must be in a master version

How to recognise a master/slave transmitter:

master: if you press any key of a master transmitter, the LED flashes before becoming steady.

slave: if you press any key of a slave transmitter, the LED goes on immediately with steady light

- 1) Press and hold button 1 and press button 2 four times at same time, Release 2 buttons till LED flashed once every three seconds
- 2) Put original remote in the front of new remote (about 2-3cm), press and hold the original remote button which need to be copied until the LED will turn on with a fixed light and then emits a double flash very 2 seconds
- 3) Pressing and hold the button 2 and 3 simultaneously of original FAAC/GENIUS to transmit the seed code
- 4) While the led of FAAC and GENIUS is flashing, put it close to new remote about 2-3cm, and press the button that you want to copy until the LED will change the frequency of flash (faster than before to confirm the correct copy the code)

V2

- 1) Press and hold button 1 and press button 2 four times at same time, Release 2 buttons till LED flashed once every three seconds
- 2) Put original remote in the front of new remote (about 2-3cm), press and hold the original remote button which need to be copied until the LED will turn on with a fixed light and then emits a double flash very 2 seconds
- 3) Press and hold once again the same button of original remote, the LED of new remote will flashes quickly, press the button that you want to save the code, until the LED off
- 4) Now active the remote with AMC procedure

Compatible List

Brand	Model	Brand	Model
ACM (AMC)	TX2, TX2 COLOR, TX4	KINGGATES	STYLO, CLIPPER
ADYX	TE4433H BLUE, 433-HG BRAVO	KLING	KUA, KUA E, KUA S
AERF	COMPACT, HY-DOM, MERCURI B, MERCURI C, SABUTON, MARS, SATURN, ST3/N, TERRA, TMP-1, TMP-2, UNITECH	LABEL	SPYCO, RJW4E
ALLMATIC (AMC)	BROWN, BROWN RED, BRO.OVER, PASS, MINIFASS	LEB	TMW
APERIO	GO, GO PRO, GO MINI	LINCE	LR2035
APERTO (SOMMER)	TX02-434-2, TX02-868-2 BLUE, 4025 TX02-868-2, 4022 TX02-434-2, 4020 TX03-434, TX-03-868-4, 4013, TX03-434-4	LIFE	LIFE FIDO2 / FIDO4 / VIP2 / VIP4 / VIP2R / VIP4R / STAR2 / STAR4 / BRAVO2 / BRAVO4
APRIMATIC (AMC)	TR2/TR4, TM4, TXM	LINEAR	MCT-11, ACT-22, ACT-21, STING RAY ACT-31, STING RAY ACT-34B
ATA	PTX4 BLUEM PTX4 PINK	MHOUSE (AMC)	GTX4, GTX4C, TX4
ASTRO		MA	TX1, TX2, TX3
AVIDSEN	104251, 104250, 104250 OLD, 104250 RED, 104257, 104350, 654250	MOOVO (AMC)	MT4G
BALLAN	FM400, FM400E, FM404B, 4013	MARANTEC	D101, D12, DIGITAL302, DIGITAL304
BENINCA (AMC)	TO.GO WV, TWV, ROLLKEY, APPLE, LOT WCV, CUPIDO, TO.GO.QV, IO, LOT2WCV, LOT1W, LOT2W, LOT4W, LOT1WM, LOT2WM, T2W, T4W	MERLIN/PROLIFT	M230T (PROLIFT), M430R (PROLIFT)
BESIDE	BEZAP, HIT	MONSEIGNEUR	ARC
		NOVA	NOVA-CENTURION 1, NOVA-CENTURION 2, NOVA-CENTURION 3, NOVA-CENTURION 4

BFT (AMC)	MITTO, MITTO M/MITTO 2M/MITTO4M, MITTO RCB/MITTO RCB02/MITTO RCB04), MITTOA(MITTO 2A/MITTO 4A), MITTO B, TRC(TRC2/TRC4), GHIBLI, MURALE, KLEIO, TE01, TE02,TE04, RB4 MURALE	NICE	SMILO, FLO-R, VERY-VR,ERA-FLOR, ONE, ERA ONE, INTI,ERGO, ON2/4/9E, ON 868 2/4,ON 24E 868 FM, PLANO
CAME	T431, T434, TOP432A, TOP434a, TOP432, TAM432SA, TOP432NA	NORMSTAHL	EA433 2KM, EA433 2KS, EA433 4K, NOO2800, RCU 433 2K, RCU 433 4K
CARDIN (AMC)	TRQ S449 (TRQ449100/TRQ449200/TRQ449300/TRQ449400), TRQ S449 GREEN(PRECODE), TXQ S449(TXQ449200/TXQ449300/TXQ449400), TXQ S449 GREEN, TRQ S486(TRQ486200/TRQ486400), TXQ S486(TXQ486200/TXQ 486200/TXQ486400), S437 TX, XRADO, S449, S476TX2, S476TX, S486	NORTON	NEO, TXCD, GO NORTON, GO MINI NORTON
		NOVOTECNICA (AMC)	BLXL2
		NOVOFERM	NOVOTRON 502-504-512MIX43-2, MTR40-2, MCHS43-2, MHS43(2-4), MNHS433(2-4), MCHS, MINI-NOVOTRON504, MICRO-NOVOTRON 502
CASALI	JA33 AMIGO, GENIUS/CASALI A252RC	NOLOGO	ECO DIP
CASIT	ERTS92B, ERTS92T, ERTS476D, ERTS200Q, ERTS476D, ERTS476Q	O&O (AMC)	T.BOM, TWIN, TX, TWIN, TX2/TX4
CELISA	S10 1, S10 2	O&G	OG62, OG64
CENTURION	CLASSIC, SMART	OPENOUT	TMQ
CHAMBERLIN/ LIFTMASTER/ MOTORLIFT	953ESTD, 371LM(315MHZ), 81LM, 971LM(390MHZ), 84330E, 94334CE, 94333E/94334E/94335E, 9747E, 1A5477, 1A6487, 132B2372, 94330EML/94333EML/94335EML, 84330EML/84333EML/84335EML, 8747EML	PECCININ	TX MENBRANA
		PORTAMATIC	MPH01, MPH02
CLEMSA	MUTANCODE, T, T-8, E-CODE N, MASTERCODE MV	PRASTEL	TC2E(4E), SLIM, BFOT, MPSTP2E, MPSTF2, MPSTF4, MPSTF2RE, MPSTF4RE, MPSTP2E, MPSTP2EBL UE
CPS	TCP3, CPS1, CPS2, CPS4	PROEM	ER4C4ACS
CYACSA	NEO, TWIN		
DASPI (AMC)	HAPPY2, POPS 2, ZERO RC(ZERO 2RC, 4RC)	PROGET	ETY_433N2, ETY_433N4
DEA	TR MIO, 133 1, 433 2, GENIE, PUNTO S2, PUNTO 278, GOLDR, GENIE R 273, GENIE R-GT2N	PROTECO	TX433, EUROMATIC
DELMA	MIXARD 433 1, MIXARD 433 2, KING 433 2	PUJOL	MARTE, P215, TWIN, VARIO, VARIO MARS, VARIOOCEAN, NEO
DETUMANDO	STANDARD		
DICKERT	MAHS433 01, MAHS433 04	QUASAR	433
DITEC (AMC)	GOL, GOL4C, BIXLS2, BIXLP2, BIXAG4, BIXLG	RIB	LITHILO
DMFA	GO, MAP, NEO		
DMIL	GO, NEO		
DOORMATIC	SAW	ROPER	NEO, GO ROPER, GO MINI ROPER
DOITRAND	MPSTF2E, JAUNE	SABUTOM	BROOVER, BROSTAR
DOORHAN	TRANSMITTER 4	SEA	SMART DIP
DUCATI	TSAW1, TSAW2, TSAW3, 124, TE2	SECULUX	NEO
ECOSTAR	RSE, RSC, RSZ	SEAV	BE HAPPY RS(BE-HAPPY-RS1, BE-HAPPY-RS2, BE-HAPPY-RS3), BE-SMART RSX, BE-HAPPY RH1, BE-HAPPY RH2, BE-HAPPY RH3
ELBE	501, 502, 504, 502A, 504A	SILVELOX	MHZ 2007, QUARZ SAW
ERREKA	IRIS, ROLLER 2, ROLLER 433, ROLLER 868, SOL433, SOL868, VEGA 433, VEGA 868	SICE	4790207
ELCA	IRIS, ASTER, ASTER 1000, ASTER 1001	SIMINOR	CVXNL, MITTO, SIM433
FAAC (AMC)	XT 433 RC, TM1 433 DS, TM2 433 DS, TM3 433 DS, 433L2, 433L4, TM2 433 SLP, TM4 433 SLP, TLM 433SLH, TLM 868SLH, DL 868SLH, XT 868SHL, XT 433SHL, T 868SHL, T 433SHL, XT433RC, TE433HG	SEUCURVERA	SV R2C, SV R4C, SV R6C
		SERAI	OG/52, OG54, OG82, OG84, OG/28, OG48, OG62, OG64
FADINI (AMC)	FADINI JUBI, JUBI SMALL, ASTRO 43 SMALL, 433 M2 ASTRO 433-2, ASTRO 433-4, JUBI2/JUBI4	SOMFY	LEIS, K-EASY, K-EASY NEW, K-EASY OLD, MITTO, KEY GO RTS, TELIS, KEYTIS RTS
FERPORT	TAC1, TAC2, TAC4, TAC 1K, TAC 2K, TAC 4K, TAC2KR		
FORSA	GO, NEO		
GIBIDI	GIBIDI OPEN TMB, OPEN OUT, AU01590, AU1600, DOMI- NO AU1680 WOOD, GIBIDI AU1610, GIBIDI AU1680, AU1810, AU03000, AU03000 DOMINO, DTC 4334, DTS4334-AU0400	SOMMER	SOMMER 4026 TX03-868-2, SOMMER 4020 TX03-868-4, SOMMER 4031, SOMMER 4025, SOMMER 4011, SOMMER 4035, APERTO 4025
GULLIVER	MDW	STAGNOLI	KALLISTO, VENUS AV223
GENIUS (AMC)	AMIGO, AMIGOLD, KILO, BRAVO, ECHO	TAU (AMC)	250K-SLIMRP, 250K-SLIMR, 250T-4RP
		TEC	GO
GENIE (AMC)	GITR-3, GIT, GICT390, GIFT390-1, G3T-BX, G1T-BX, GM3T, GICTD, GIFTD	TELCOMA	FM402, FM402E, FM400E, FM400
HORMANN	H5M2, H5M4	TORLIFT	TORMIT4
HYDOM	GO		
JAY	UBEI X 15L1, UBET 21, UBET 41, UBET 61	VDS (AMC)	TRQ P, ECO-R
		VARWFORD	EA433 4K, SMART2, SMART3
JCM GO	DML GO, ALFA TORRES GO, HIBRID GP, HYDOM GO, PUERTAS CAREN GO, FORSA GO, TECH FO, BALEATO GO, CYACSA DO, ELEMAT GO, PORTIS GO, GIB GO		
KBLUE	ETH-TELO1	V2 (AMC)	V2 PHOX 2, V2 PHOX 4, V2 PHOENIX 2, V2 PHOENIX 4, V2 TXC, V2 TRC, V2 TSC4, V2 HAND
KEY	900TXB-42R, SUB44, TXB-44R, TXG-44R		